

### ORDER CODES

**Example Order Number:**

77T-662C - D - 33 - 85 - 85 - A - U - S(0-200) C

#### 1-0 Transmitter Type

CODE	DESCRIPTION
77T-662C	(4 to 20) mA HART® Field Transmitter with dual-cavity explosion-proof aluminum housing FM/CSA XP Class I Div I Groups B,C,D; DIP Class II Div I Groups E,F,G; Class III; NI Class I Div II Groups B,C,D
77T-662E	(4 to 20) mA HART® Field Transmitter with dual cavity flame-proof/dust-protected aluminum housing ATEX/IECEx; Ex d IIC T6...T4Gb; Ex tb IIIC T110 °C Db, IP66/67
T82-00	(4 to 20) mA dual input, isolated HART® head-mounted Transmitter
76T82	(4 to 20) mA dual input HART® programmable Transmitter with digital display and explosion-proof aluminum housing, FM/CSA,NI,IS,XP,DIP Class I Div I and Div II, Groups A,B,C,D

#### 1-1 Housing Cover Options

CODE	DESCRIPTION
T	Solid cover for 662 series
D	Glass cover with digital display for 662 series
D10	Glass cover with digital display for 36T82 and 76T82 series

#### 1-2 Configuration Input

CODE	DESCRIPTION
00	T82 Unconfigured
01	662 Single input, unconfigured
02	662 Dual input, unconfigured
21	Ch1: RTD 2-wire, Ch2: inactive
22	Ch1: RTD 2-wire, Ch2: RTD 2-wire
23	Ch1: RTD 2-wire, Ch2: RTD 3-wire
2T	Ch1: RTD 2-wire, Ch2: Thermocouple
31	Ch1: RTD 3-wire, Ch2: inactive
32	Ch1: RTD 3-wire, Ch2: RTD 2-wire
33	Ch1: RTD 3-wire, Ch2: RTD 3-wire
3T	Ch1: RTD 3-wire, Ch2: Thermocouple
41	Ch1: RTD 4-wire, Ch2: inactive
4T	Ch1: RTD 4-wire, Ch2: Thermocouple
TI	Ch1: Thermocouple, Ch2: inactive
TT	Ch1: Thermocouple, Ch2: Thermocouple

**For complete transmitter specifications  
see Transmitter Section.**

HART® is a registered trademark of HART Communication Foundation.

#### 1-1 Transmitter Type

1-0  
77T-662C - D - 33

1-2  
85 - 85

1-3

1-4

1-5

1-6

1-7

1-8

#### 1-8 Unit of Measure

CODE	DESCRIPTION
C	Celsius
F	Fahrenheit

#### 1-7 Range

CODE	DESCRIPTION
S	(lower limit – upper limit)

#### 1-6 Failure Mode

CODE	DESCRIPTION
U	Upscale Burnout $\geq$ 20.5 mA
D	Downscale Burnout $\leq$ 3.8 mA

#### 1-5 Input Set-ups

CODE	DESCRIPTION
0	One Input (662 only)
A	Process Variable = Ch1; CH2 = inactive
B	Process variable = CH1; secondary variable = Ch2 (T82 Only)
C	Process variable = the difference between CH1 and Ch2
D	Process variable = the average between CH1 and Ch2
E	Sensor backup; Process variable= Ch1 and Ch2

#### 1-4 Sensor Input Channel 2

CODE	DESCRIPTION
J	Type J thermocouple
K	Type K thermocouple
T	Type T thermocouple
N	Type N thermocouple
E	Type E thermocouple
85	100 ohm platinum ( $\alpha = 0.00385 \text{ }^{\circ}\text{C}^{-1}$ )
00	No second channel

#### 1-3 Sensor Input Channel 1

CODE	DESCRIPTION
J	Type J thermocouple
K	Type K thermocouple
T	Type T thermocouple
N	Type N thermocouple
E	Type E thermocouple
85	100 ohm platinum ( $\alpha = 0.00385 \text{ }^{\circ}\text{C}^{-1}$ )